

Product data sheet

Specifications



APC Smart-UPS SRT 48V 1kVA 1.5kVA RM Battery Pack



SRT48RMBP

Overview

Lead Time Usually in Stock

Main

Number Of Rack Unit 2U

Battery Type Lead-acid battery

Provided Equipment Documentation CD
Installation guide
Rack mounting brackets
Warranty card

Batteries & Runtime

Number Of Battery Free Slots 0

Number Of Battery Filled Slots 0

Device Mounting Stand alone battery stack

Battery Voltage 48 V

Number Of Battery Replacement Quantity 2

Replacement Battery [APCRBC155](#)

Physical

Colour Black

Height 3.35 in (8.5 cm)

Width 17.01 in (43.2 cm)

Depth 21.10 in (53.6 cm)

Net Weight 65.92 lb(US) (29.9 kg)

Mounting Mode Rack-mounted

Environmental

Ambient Air Temperature For Operation 32...104 °F (0...40 °C)

Operating Altitude 0...10000 ft

Relative Humidity 0...95 % non-condensing

Ambient Air Temperature For Storage 5...113 °F (-15...45 °C)

Storage Altitude 0...50000 ft (0.00...15240.00 m)

Storage Relative Humidity 0...95 % non-condensing

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	9.61 in (24.4 cm)
Package 1 Width	29.49 in (74.9 cm)
Package 1 Length	23.39 in (59.4 cm)
Package 1 Weight	81.57 lb(US) (37 kg)

Contractual warranty

Warranty	2 years repair or replace
----------	---------------------------

Sustainability

Green Premium™ label is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

[Learn more about Green Premium >](#)



Energy Efficient Take-back Transparency RoHS/REACH

Resource performance

Energy Efficient Product

Take-Back Program Available

Well-being performance

Mercury Free

Rohs Exemption Information [Yes](#)

Certifications & Standards

Reach Regulation [REACH Declaration](#)

Eu Rohs Directive [Compliant with Exemptions](#)

Environmental Disclosure [Product Environmental Profile](#)

Circularity Profile [End of Life Information](#)
